



CHANGEMENT DU VOLTAGE DE 115V À 230 V JS0502-1 / JS0752-1 / JS1002-1

EMERSON™
Motor Technologies

CAT. NO. JS0752-1
JET PUMP
ASSEMBLED IN MEXICO DUTY

MODEL C55CXJWJ-4721 CAT JS0752-1
SF 1.65 VOLTS 230/115 HZ 60
HP 3/4 RPM 3450 DUTY CONT.
AMPS 5.8/11.6 INS CLASS B
SF AMPS 7.4/14.8 AMB 40 °C
HP RPM CODE L PH 1
AMPS MFG NO G09C
SF AMPS FRAME 56Y
THERMALLY PROTECTED AUTO

SUITABLE FOR FIELD WIRING
USE COPPER CONDUCTORS ONLY

CONNECTIONS
LOW VOLTAGE HIGH VOLTAGE

MOTOR IS NON-REVERSIBLE
CCW ROTATION SHAFT END

SP® LR63596



WARNING : MOTOR MUST BE GROUNDED IN ACCORDANCE WITH LOCAL AND NATIONAL ELECTRIC CODES. COMPONENT COVER MUST BE IN PLACE BEFORE OPERATING TO PREVENT ELECTRICAL SHOCK OR INJURY.

Étape 1

Prendre le fil BRUN et le mettre à la position # 6 sur la borne de plastique.

Étape 2

Prendre le fil BLANC et le mettre à la position # 3 (à la position du fil BRUN)